



# Professional Commercial FM Transceiver

- Channel Scan / Priority Scan
- Time-out Timer
- Talk Around
- Low Battery Alert
- Squelch Level Checking
- Busy Channel Lock Out
- Output Power Checking
- Wide / Narrow Bandwidth Setting



UHF:400-470MHz

## LS-V6

Battery Save **16 Channels** **VOX** **Scrambler**

CN/English Voice Announcement  
PC Program Encryption  
Non-standard CTCSS/DCS Program



www.cnlisheng.com



### Main Function

- Channel Scan / Priority Scan
- Scramble
- Talk Around
- Time-out Timer
- Voice Announcement
- Battery Save
- Squelch Level Checking
- Low Battery Alert
- Output Power Checking
- Busy Channel Lock Out
- VOX
- Wide / Narrow Bandwidth Setting



### Specification

GENERAL	
Number of Channels	16
Operating Voltage	3.7V DC
Operating Temperature	-10°C ~ +50°C
Weight	159g (Including battery and antenna)
Dimension	180mm x 58mm x 35mm (Including antenna)
TRANSMITTER	
Frequency Range	400.000-470.000MHz,
Sensitivity	≤0.2μV
Narrow band	≤16KHz
Adjacent Channel Selectivity	≥65dB
Intermodulation	≥55dB
Audio power output	> 500m W
Audio Distortion	≤10%
Frequency tolerance	5ppm
Receives the current	Standby 60mA Call 150Ma
Audio Response (300-3400Hz)	+1~-3dB
RECEIVER	
Frequency Range	400.000-470.000MHz
Radio frequency power	≤2.2W
Modulation type	FM
Stray power	≤7.5μW
Modulation noise	<-40dB
Modulation distortion	<5%
frequency tolerance	5ppm
largest deviation	≤±5KHz
Emission current	≤1200mA
Audio Response (300-3400Hz)	+1~-3dB
Adjacent Channel	≥65dB

Note: The above specifications are upon the TIA/EIA-603 standard, and subject to change without notice, for the developing of technology.

### Standard Accessories



Charger



Battery



Belt Clip



Antenna



Hand strap

### Lisheng Communications Co., Ltd.

Add.: (CHONGXIANG ST. EAST SEGMENT) QINGMENG TECH & INDUSTRY AREA, QUANZHOU ECON. & TECH., QUANZHOU FUJIAN, CHINA.

Tel.: +86-(0)595-2241 9992 / 2241 9993 Fax.: +86-(0)595-2248 1909